



Prodigi for Windows

***Technical Requirements and Specifications**

Software Requirements: The following are suggested *minimum requirements* for using Prodigi software with user-supplied hardware.

Computing Device (tablet, laptop, or PC)

| Description | Specification |
|--|---|
| Operating System (64-bit) | Windows 11, Windows 10 |
| Processor** | Intel Core i3 (4 CPUs) or better CPU |
| Memory (RAM) | At least 8 GB |
| Required hard disk space | 8 GB free disk space |
| Video | DirectX 11 or newer |
| Sound | Windows-compatible sound card (for speech). |
| <i>**ARM64 may not support the optional Kodak distance camera.</i> | |

Document Camera***

| Description | Specification |
|--|----------------------|
| Operating System | Windows 10+ |
| Resolution | 13MP |
| Color | 24-bit color |
| FPS | 60fps@1080P |
| Connectivity | USB connectivity |
| <i>***Prodigi is optimized for the Solo 8+. Results may vary with other cameras.</i> | |

Internet: Required for installation, activation, some features (example – Books), and ongoing updates.

URL Whitelist: The following URLs must be whitelisted for proper functionality in restricted networks:

- <https://hgphcardsad01.blob.core.windows.net/>
- <https://id.humanware.com>
- <https://humanware.ca/>



******Hardware Specifications:** The following are the basic specifications for the hardware sold with the Prodigi Starter Kit, Complete Kit, and All-in-One configurations.

Hovercam Solo 8+

| Description | Specification |
|-------------------|--|
| Resolution | 4224 x 3156; 13MP |
| Color | 24-bit color |
| FPS | 4K @30fps, 1080p @60fps, 720p @120fps |
| Operating System | Windows 10+ |
| Connectivity | USB 3.0 |
| Dimensions | 1.5 x 3.5 x 11.4" 3.8 cm x 9 cm x 29 cm Extended: 19.56" /49.75 cm |
| Weight | 2.2 lbs /1.0 kg |
| Service & Support | Hovercam 2-year parts and labor warranty |

[Click here for complete Solo 8+ specifications.](#)

Microsoft Surface Pro 9

| Description | Specification |
|-------------------|---|
| Operating System | Windows 11 Pro |
| CPU | Intel Core i5 (12th Gen) 1245U / 1.6 GHz |
| Memory (RAM) | 8GB; LPDDR5 SDRAM |
| Storage | 128GB SSD |
| Display | 13" touchscreen (10-point multi-touch) 2880 x 1920 |
| Audio & Video | Intel Iris Xe Graphics Cameras: 4K (rear); 1080p (front) Resolution: 10 Megapixel (rear) Stereo speakers, dual far-field studio microphones Dolby Atmos compliant |
| Wireless | Bluetooth 5.1, 802.11a/b/g/n/ac/ax (Wi-Fi 6E) |
| Battery | Up to 15.5 hours |
| Connections | 2 x USB4 (supports Thunderbolt 4) (Type C) |
| Dimensions | WxHxD: 11.3 x 8.2 x 0.4" WxHxD: 28.7 x 20.8 x 1.0 cm |
| Weight | 31oz. / 878.8g |
| Service & Support | Microsoft Limited warranty - 1 year |

[Click here for full Microsoft Surface Pro specifications.](#)



Prodigi software

powered by HumanWare

AOC 24" All-in-One PC (available in North America only)

| Description | Specification |
|--------------------|---|
| Operating System | Windows Pro 11 |
| Processor | Intel® Core™ i3-12100 |
| Memory | DDR 16GB |
| Storage | 512GB SSD |
| LED Monitor | 23.8", IPS Full HD, 1920x1080, matte |
| Network | Realtek 8111EL&F 100/1000M Ethernet,RJ45 port |
| Audio | Realtek ALC662, Azalia Code support 5.1 channel output, 2 Jacks, MIC in/Line out |
| Wi-Fi | 802.11b/g/n/ac 2.4GHz & 5GHz Dual Band WIFI 5 and Bluetooth 4.0 |
| Speakers | Two 3W Height adjustable stand with quick release function |
| Webcam | 3MP |
| Keyboard and Mouse | AOC USB |
| Power Adapter | 13.5/19V |
| UPS Battery | 60 minutes |
| Input/Output | 1 line out and 1 Mic in, COM Port, 2 - USB 2.0 Ports, 4 USB 3.0 Ports, LAN RJ45, HDMI, DC-In port |
| Dimensions | Monitor: 23.9" diagonal and (HxW) 13.5 x 21.25" Monitor: 60.7cm diagonal and (HxW) 34.3 x 54.0cm Assembled PC (DxHxW): 8 x 14.5-19.5 x 21.25" Assembled PC (DxHxW): 20.3 x 36.8 x 54cm |
| Weight | Assembled PC: ~11.9lbs / 5.4kg Assembled PC, keyboard, and mouse: ~18.0lbs / ~8.2kg |

**Specifications and requirements are subject to change at any time.*

*****HumanWare reserves the right to substitute hardware with equal or greater specifications at any time.*